

**IN THE CLAIMS:**

Cancel claims 3-4 and 7-11 without prejudice or disclaimer and before calculating the filing fee as shown in the following listing of claims, which replaces all prior versions and listings of claims.

1. (original) A magnetic bearing device, characterized in that the magnetic bearing device comprises:

a rotor;

a plurality of electromagnets for controlling a radial position and/or an axial position of the rotor;

a power source for supplying power to the electromagnets;

a common node commonly connected to each one end of the electromagnets;

switch means for switching a voltage of the common node; and

excitation control means for controlling excitation of each of the electromagnets by a supply current supplied from the other end of one of the electromagnets to a negative electrode of the power source, or by a regenerated current regenerated from the other end of one of the electromagnets to a positive electrode of the power source, and in that:

the switch means includes:

a first switch element for connecting and disconnecting between the positive electrode and the common node; and

a first rectifier element for causing a current to flow from the negative electrode to the common node; and

the excitation control means includes:

a second switch element for connecting and disconnecting between the other end of one of the electromagnets and the negative electrode; and

a second rectifier element for causing a current to flow from the other end of one of the electromagnets to the positive electrode.

2. (original) A magnetic bearing device, characterized in that the magnetic bearing device comprises:

a rotor;

a plurality of electromagnets for controlling a radial position and/or an axial position of the rotor;

a power source for supplying power to the electromagnets;

a common node commonly connected to each one end of the electromagnets;

switch means for switching a voltage of the common node; and

excitation control means for controlling excitation of each of the electromagnets by a supply current supplied from a positive electrode of the power source to the other end of one of the electromagnets, or by a regenerated current regenerated from a negative electrode of the power source to the other end of one of the electromagnets, and in that:

the switch means includes:

a first switch element for connecting and disconnecting between the common node and the negative electrode; and

a first rectifier element for causing a current to flow from the common node to the positive electrode;

and the excitation control means includes:

a second switch element for connecting and disconnecting between the positive electrode and the other end of one of the electromagnets; and

a second rectifier element for causing a current to flow from the negative electrode to the other end of one of the electromagnets.

3.-4. (canceled)

5. (original) A magnetic bearing device, characterized in that the magnetic bearing device comprises:  
a rotor;

a plurality of electromagnets for controlling a radial position and/or an axial position of the rotor;

a power source for supplying power to the electromagnets;

a common node commonly connected to each one end of the electromagnets;

switch means for switching a voltage of the common node;

a first excitation control means for controlling excitation of at least one of the plurality of electromagnets by a supply current supplied from the other end of one of the electromagnets to a negative electrode of the power source, or by a regenerated current regenerated from the other end of one of the electromagnets to a positive electrode of the power source; and

a second excitation control means for controlling excitation of electromagnets other than the at least one electromagnet controlled through excitation by the first excitation control means, by a supply current supplied from the positive electrode to the other end of another one of the electromagnets, or by a regenerated current regenerated from the negative electrode to the other end of the another one of the electromagnets, and in that:

the switch means includes:

a switch element for connecting and disconnecting between the common node and the negative electrode, and a switch element for connecting and disconnecting between the positive electrode and the common node; and

a rectifier element for causing a current to flow from the common node to the positive electrode, and causing a current to flow from the negative electrode to the common node, respectively;

the first excitation control means includes:

a switch element for connecting and disconnecting between the other end of one of the electromagnets and the negative electrode; and

a rectifier element for causing a current to flow from the other end of the one of the electromagnets to the positive electrode; and

the second excitation control means includes:

a switch element for connecting and disconnecting between the positive electrode and the other end of another one of the electromagnets; and

a rectifier element for causing a current from the negative electrode to the other end of the another one of the electromagnets.

6. (original) The magnetic bearing device according to claim 5, characterized in that the current caused to flow through each of the electromagnets is increased, decreased, or maintained to be constant by adjusting a switching phase of the switch means and control phases of the first excitation control means and the second excitation control means within a common control cycle.

7.-11. (canceled)